

# **OFFICE 100 OMNI**

**SKU:** 50 Ohm: 472060 75 Ohm: 473060

#### **FEATURES**

- Ideal amplifier system for small businesses and warehouses
- Covers up to 8,000 square feet
- Includes LED indicators
- Is FCC approved and works on all U.S. carrier networks, including Verizon, AT&T, T-Mobile, UScellular, and more





### KIT INCLUDES

<b>472060</b> 50 Ohm Kit	Office 100 Amplifier	Omni Plus Antenna 314422	Inside Dome Antenna 304412	Lightning Surge Protector 859902	2ft Low-Loss Wilson400 Cable 952302	60ft Low-Loss Wilson400 Cable 952360	75ft Low-Loss Wilson400 Cable 952375
<b>473060</b> 75 Ohm Kit	Office 100 Amplifier	Omni Plus Antenna 314423	Inside Dome Antenna 304419	Lightning Surge Protector 859992	2ft Low-Loss RG11 Cable 951127	60ft Low-Loss RG11 Cable 951160	75ft Low-Loss RG11 Cable 951175

### **ABOUT**

weBoost **Office 100 Omni** is an ideal amplifier solution for small businesses and warehouses up to 25,000 sq. ft. With Office 100, anyone who walks into the business will enjoy fewer dropped calls, uninterrupted texts, better voice quality, improved hotspot capability, faster internet speeds, better streaming, and more. All components needed for do-it-yourself installation are included. Office 100 is 5G compatible and improves cell signal on all U.S. carrier networks, including Verizon, AT&T, T-Mobile, UScellular, and more. Office 100 comes with an industry-leading 3-year manufacturer's warranty and a 30-day money-back guarantee.


# **™WARNING:** This product can expose you to chemicals including Nickel, which is known to the State of California to cause cancer, and Bisphenol A, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

### **SPECIFICATIONS**

SKU NUMBER	472060† / 473060†			
FREQUENCIES	Band 12/17	700 MHz		
	Band 13	700 MHz		
	Band 5	850 MHz		
	Band 4	1700/2100 MHz		
	Band 25/2	1900 MHz		
MAX GAIN	72 dB			
MAX UPLINK POWER	24 dBm			
MAX DOWNLINK POWER	12 dBm			
IMPEDANCE	50 Ohm / 75 Ohm			
POWER	110-240V AC, 50-60 Hz, 20 W			
CONNECTORS	N-Female / F-Female			
BOOSTER DIMENSIONS	6 × 6 × 1.8 in			
BOOSTER WEIGHT	1.9 lbs			

## we:boost

### **HOW IT WORKS**



- Outside antenna: The outside antenna communicates back and forth with nearby cell towers.
- Booster: The booster amplifies any cell signals it receives from the outside antenna.
- Inside antenna: The inside antenna broadcasts these signals for use throughout your business.

### **PACKAGE DIMENSIONS**

13 L x 13 W x 15 H



**FRONT** 

13 in. x 15 in. 13 in. x 13 in.



WEIGHT

SIDE TOP

TOP/BOTTOM

SUPPORT



3-Year Warranty from Purchase.

**MASTER CARTON:** 13 L x 13 W x 15 H | 16 Lbs. | Qty 1





**UPC** 





472060 • 473060\_Office100\_SS\_112023