

# **Dual Feed**

#### **Description**

The Chaparral Dual Feed feedhorn is an orthomode transducer for simultaneous reception of horizontal and vertical C-Band polarities. Due to its reliable performance with virtually no signal loss, Chaparral's Dual Feed is the most trusted feedhorn for commercial applications.

### **Applications**

- SMATV
- Cable TV operators
- Multiple receiver systems
- Commercial satellite systems

#### **Features**

- 100% tested
- Adjustable scalar ring
- Cast-in f/D gauge
- Mounts to all standard satellite dishes
- Cast aluminum construction
- Chip-resistant polyurethane powder coating
- Two-year warranty
- Made in the USA

## **Specifications**

Part Number 11-1329-1 Frequency Range 3.7-4.2 GHz **VSWR** 1.5:1 Max f/D Range .33 to .45 Cross Pol. Isolation 35 dB Min Output Ports WR 229 Compatible Temperature Range -40° C to +60° C Size 8.0" x 6.5" x 5.0" Weight 2.23 lbs.